

7 upgrade steps :

1. Make sure the device is fully charged.
2. Download the appropriate files from the [Honeywell Software Download Center](#) .
3. Copy “eda50-ota-207.0x.00.00yy.zip” or “eda50k-ota-208.0x.00.00yy.zip” (depending on the device) to an SD card.
 - a. x = 1, if GMS version
 - b. x = 2, if non-GMS version
 - c. yy is the maintenance version
4. Power the device to insert the SD card into the slot located in the battery compartment.
5. When the device is off, press and hold the power button and the volume up button until the device vibrates, then release (this may take a few seconds).
6. The unit must boot into the Android recovery menu.
7. Use the "volume up" and "volume down" buttons to navigate the options and use the "power button" to select an option. Follow steps a, b, c, and d from the bottom in that order; the unit will remain in the recovery menu until you decide to restart.
 - a. "Erase data/factory reset" > 'Yes, delete all user data'
 - b. 'Clear cache partition'
 - c. "Apply update from SD card" > Navigate to “eda50-ota-207.0x.00.00yy.zip” or “eda50k-ota-208.0x.00.00yy.zip” (using the volume keys to move and the power key to select) and select it to start the update.
 - d. Restart the system now
8. Once the device finally restarts in the operating system
9. If you are using an older version of the operating system, please read the notes below.
10. Remove the SD card from the device.

Note:

Starting with kernels 207.0x.00.0016 (EDA50) and 208.0x.00.0016 (EDA50k), no license is required to upgrade the unit from Android 4.4 to Android 7. If an older kernel is used, ensure that the appropriate license is purchased (part number: 454-084-001) and that the license XML file is created using Honeywell License Manager (LM). The license .xml file must be copied via USB to the root of the internal storage.

RELATED ARTICLES

- [EDA50 - Unable to upgrade from Android 4.4 OS version 205.01.00.0009 to Android 7 OS version 207.01\(02\).00.0016 or later...](#)

Number of views : 3

- [How to downgrade from Android 7 to Android 4.4](#)

Number of views : 7

- [Keyboard remapping function](#)

Number of views : 2

- [How to upgrade the device firmware using Safety Suite Device Configurator ?](#)

Number of views : 2.84K

- [Steps to upgrade CT40, CT60 or CN80 from Android 7 to Android 8](#)

Number of views : 81